

Schneider Electric - Galaxy VL UPS 500 kW 400/480V Startup 5x8 : GVL500KDS

Specifications	
ENERGY STAR Unique ID:	2384013
Brand Name:	Schneider Electric
Model Name:	Galaxy VL UPS 500 kW 400/480V Start-up 5x8
Model Number:	GVL500KDS
Power Conversion Mechanism:	Static
Minimum Configuration Tested Model Number:	GVL200K500DS
Active Output Power Rating Minimum Configuration (W):	200000
Apparent Output Power Rating Minimum Configuration (VA):	200000
Maximum Configuration Tested Model Number:	GVL500KDS
Active Output Power Rating Maximum Configuration (W):	500000
Topology (ac):	Multi-Mode Double Conversion
Topology and Product Type Combined:	ac - Other
Application:	Data Center
Rated Input Voltage (V rms):	380-480
Rated Input Frequency (Hz):	50-60
Rated Output Voltage (V):	380-480
Rated Output Frequency (Hz):	50-60
Rack Mountable:	No
Height (mm):	1970
Width (mm):	850
Depth (mm):	925
Normal Mode(s) Input Dependency Characteristic (ac):	Voltage and Frequency Independent, Voltage and Frequency Dependent
Modular UPS:	Yes
Number of Normal Modes:	Multiple-normal-mode
Default Normal Mode (ac):	Voltage and Frequency Independent
Test Input Voltage (V rms):	480
Test Input Frequency (Hz):	60
Test Output Voltage (V):	480

Test Output Frequency (Hz): 60 Total Input Power in W at 0% Load Min Config Lowest Dependency (ac): Total Input Power in W at 0% Load Min Config Highest Dependency (ac): Efficiency at 25% Load Min Config Lowest Dependency (ac): Efficiency at 25% Load Min Config Highest Dependency (ac): Efficiency at 50% Load Min Config Lowest Dependency (ac): Efficiency at 50% Load Min Config Lowest Dependency (ac): Efficiency at 50% Load Min Config Highest Dependency (ac): Efficiency at 50% Load Min Config Highest Dependency (ac): Efficiency at 75% Load Min Config Lowest Dependency (ac): Efficiency at 75% Load Min Config Highest Dependency (ac): Efficiency at 75% Load Min Config Highest Dependency (ac): Efficiency at 100% Load Min Config Lowest Dependency (ac): Efficiency at 100% Load Min Config Lowest Dependency (ac):
Lowest Dependency (ac): Total Input Power in W at 0% Load Min Config Highest Dependency (ac): Efficiency at 25% Load Min Config Lowest Dependency (ac): Efficiency at 25% Load Min Config Highest Dependency (ac): Efficiency at 50% Load Min Config Lowest Popendency (ac): Efficiency at 50% Load Min Config Highest Dependency (ac): Efficiency at 50% Load Min Config Highest Dependency (ac): Efficiency at 75% Load Min Config Lowest Popendency (ac): Efficiency at 75% Load Min Config Lowest Popendency (ac): Efficiency at 75% Load Min Config Highest Popendency (ac): Efficiency at 75% Load Min Config Highest Popendency (ac): Efficiency at 75% Load Min Config Highest Popendency (ac): Efficiency at 100% Load Min Config Lowest Popendency (ac):
Highest Dependency (ac): Efficiency at 25% Load Min Config Lowest Dependency (ac): Efficiency at 25% Load Min Config Highest Dependency (ac): Efficiency at 50% Load Min Config Lowest Dependency (ac): Efficiency at 50% Load Min Config Lowest Dependency (ac): Efficiency at 50% Load Min Config Highest Dependency (ac): Efficiency at 75% Load Min Config Lowest Popendency (ac): Efficiency at 75% Load Min Config Highest Dependency (ac): Efficiency at 75% Load Min Config Highest Popendency (ac): Efficiency at 75% Load Min Config Highest Popendency (ac): Efficiency at 100% Load Min Config Lowest Popendency (ac):
Dependency (ac): Efficiency at 25% Load Min Config Highest Dependency (ac): Efficiency at 50% Load Min Config Lowest Dependency (ac): Efficiency at 50% Load Min Config Highest Dependency (ac): Efficiency at 75% Load Min Config Lowest Dependency (ac): Efficiency at 75% Load Min Config Highest Dependency (ac): Efficiency at 75% Load Min Config Highest Dependency (ac): Efficiency at 75% Load Min Config Highest Dependency (ac): 99.4 99.4
Dependency (ac): Efficiency at 50% Load Min Config Lowest Dependency (ac): Efficiency at 50% Load Min Config Highest Dependency (ac): Efficiency at 75% Load Min Config Lowest Dependency (ac): Efficiency at 75% Load Min Config Highest Dependency (ac): Efficiency at 75% Load Min Config Highest Dependency (ac): 97.2 99.4 99.4 99.4
Dependency (ac): Efficiency at 50% Load Min Config Highest Dependency (ac): Efficiency at 75% Load Min Config Lowest Dependency (ac): Efficiency at 75% Load Min Config Highest Dependency (ac): Efficiency at 100% Load Min Config Lowest 99.4
Dependency (ac): Efficiency at 75% Load Min Config Lowest Dependency (ac): Efficiency at 75% Load Min Config Highest Dependency (ac): Efficiency at 100% Load Min Config Lowest 97.2
Dependency (ac): Efficiency at 75% Load Min Config Highest Dependency (ac): Efficiency at 100% Load Min Config Lowest 99.4 97.2
Dependency (ac): Efficiency at 100% Load Min Config Lowest 97.2
/
Efficiency at 100% Load Min Config Highest 99.5 Dependency (ac):
Weighted Efficiency Calc Min Config Lowest 96.9 Dependency:
Weighted Efficiency Calc Min Config Highest 99.2 Dependency:
Minimum Configuration Input Power Factor 0.99 Highest-Input Dependency:
Total Input Power in W at 0% Load Max Config Lowest Dependency (ac): 1952.82
Total Input Power in W at 0% Load Max Config 899.06 Highest Dependency (ac):
Efficiency at 25% Load Max Config Lowest Dependency (ac): 96.4
Efficiency at 25% Load Max Config Highest 99.0 Dependency (ac):
Efficiency at 50% Load Max Config Lowest Dependency (ac): 97.1
Efficiency at 50% Load Max Config Highest 99.3 Dependency (ac):
Efficiency at 75% Load Max Config Lowest Dependency (ac): 97.2
Efficiency at 75% Load Max Config Highest 99.4 Dependency (ac):
Efficiency at 100% Load Max Config Lowest Dependency (ac): 97.1
Efficiency at 100% Load Max Config Highest 99.4 Dependency (ac):
Weighted Efficiency Calc Max Config Lowest Dependency: 96.9
Weighted Efficiency Calc Max Config Highest 99.3 Dependency:

aximum Configuration Input Power Factor owest-Input Dependency: aximum Configuration Input Power Factor ighest-Input Dependency: ficiency (%): 96.	
ighest-Input Dependency: ficiency (%): 96.	
, ,	۵
	9
odular UPS Module Tested Model Number: 0G-	G-PM50KD2
nergy Storage Mechanism: Bat	ittery
nergy Storage System Technology: Val	lve Regulated Lead-acid Battery
nergy Storage System Configuration: Sep	parate Enclosure
nergy Storage System Removable to Another Yes	s
nergy Storage System Runtime at 100% Load N/Anin.):	'A
nergy Storage System Runtime at 50% Load N/Anin.):	'A
nergy Storage System Warranty (yrs): N/A	'A
nergy Storage System Information URL: N/A	'A
	tps://www.apc.com/us/en/who-we-are/sustainability/recycling- tions.jsp
etwork Connections Available: Ser	rial Port,Ethernet
ommunication Protocols:	TTP,HTTPS,Modbus TCP,SNMP (v1, 2 or 3),Modbus RTU
anufacturer Take Back Program: Yes	s
	tps://www.apc.com/us/en/who-we-are/sustainability/recycling- tions.jsp
odel Web Page URL: http	tps://www.apc.com/shop/us/en/products/P-GVL500KDS
est Method Guidelines: http	tps://www.apc.com/us/en/who-we-are/sustainability/
ate Available on Market: 202	21-04-03
ate Certified: 202	21-07-06
arkets: Uni	nited States, Canada
NERGY STAR Certified: Yes	s

Additional Model Information

Galaxy VL UPS 500 kW, 400/480V, GVL 500KD,

UPC Codes 731304423072, 731304423089

Captured On: 05/02/2025